

**BELKIN®**

**Hi-Speed USB 2.0  
Premium Hub**

Guarantees superior  
connection for all USB 1.1  
and USB 2.0 devices

EN



**User Manual**

**F5U231vuk1**

## Table of Contents

---

<b>Introduction .....</b>	<b>1</b>
<b>Overview.....</b>	<b>2</b>
Features.....	2
Package Contents .....	3
Technical Specifications .....	3
<b>Overview.....</b>	<b>3</b>
<b>Installation .....</b>	<b>4</b>
<b>Connecting USB devices to the Hub .....</b>	<b>5</b>
<b>Determining the speed of connected devices .....</b>	<b>6</b>
<b>Information.....</b>	<b>7</b>

### Welcome to Belkin USB 2.0!

Congratulations and thank you for purchasing the Belkin Hi-Speed USB 2.0 Premium hub. The Hub provides four downstream USB ports that offer backward-compatible, Plug-and-Play connectivity with all USB devices, including USB 1.1 (or low- and full-speed) devices, as well as with USB 2.0 (or high-speed) devices. This includes such peripherals as scanners, printers, mass-storage devices, and high-resolution cameras. The Hub is self-powered, which allows the cascading of devices with additional hubs, so that up to 127 USB devices may be connected to a single port.

EN

The Hub features multicolor LEDs that indicate the operating speed of each connected USB device and the speed of the link to the host computer. For additional information, refer to the “Technical Specifications” section.

The Premium hub offers several important advantages over traditional USB 2.0 hubs. Most important is its implementation of the new “Quad TT” architecture. Simply stated, when connected to a USB 2.0 host controller, each of the Premium hub’s four downstream ports deliver a full 12Mbps of USB bandwidth for low- and full-speed devices while still providing total support for high-speed devices. This is especially important when connecting multiple, bandwidth-intensive, full-speed devices such as USB webcams, speakers, scanners, and external storage devices.

## Overview

---

In contrast, a traditional four-port USB 2.0 hub provides only 12Mbps of bandwidth for use by low- and full-speed devices, and this bandwidth is shared by each of the four ports. The Premium hub delivers up to 48Mbps of bandwidth, 12Mbps for each port!\*

In addition to the “Quad TT” feature, the Premium hub also monitors the speed of each connected device and provides users with a visual indication of its connected speed. Refer to the “Determining the Speed of Connected Devices” section of this User Manual for additional information.

EN

\*In cases in which the Premium hub is connected to a USB 1.1 host controller, the maximum USB 1.1 bandwidth of 12 Mbps is shared across all four ports.

### Features

- Speed-sensing LED indicator for each individual port
- Advanced Quad TT architecture for low- and full-speed devices
- Four 480Mbps downstream ports
- Operates without power supply with most USB devices
- Multiple hubs may be stacked one upon the other
- Compliant with Universal Serial Bus specification 2.0 (data rate 1.5/12/480Mbps)
- Backward-compatible with Universal Serial Bus specification 1.1 (data rate 1.5/12Mbps)
- Compatible with Windows® 98 SE, Me, 2000, and XP
- Approved by USB Implementers Forum (USB-IF)
- Supports Plug-and-Play specifications
- Supports “hot swapping” of USB devices
- Over-current detection and protection
- Fully compatible with USB 1.1 and USB 2.0 devices

### Package Contents

- High-Speed USB 2.0 Premium hub
- C Power Adapter
- User Manual

### Technical Specifications

Upstream Ports	(1)
Downstream Ports	(4)
Per-Port Voltage	DC +5V
Per-Port Current	500mA (max) (self-powered mode)
Power Mode	Self-powered/bus-powered
Operating Temperature	5° C ~ 40° C
Storage Temperature	-20° C ~ 60° C
Enclosure	ABS plastic

### Power Supply

Output:	DC 6V 2.1A
Plug Size:	5mm (outer) 2mm (center)
Plug Polarity:	Center Positive

### Upstream Port LED

Color Definitions:	
Red	Full-speed (12Mbps)
Amber	High-speed (480Mbps)

### Downstream Port LED

Color Definitions:	
Green	Low-speed (1.5Mbps)
Red	Full-speed (12Mbps)
Amber	High-speed (480Mbps)

## Installation

---

**Important Note:** Please do not connect any USB devices to the Hub until instructed to do so in step 4 of this installation procedure.

1. Plug the AC adapter into a wall outlet or surge suppressor. Plug the DC connector into the DC power jack found on the rear of the Hub.

**Note:** The Hub may be used without the power supply with most USB devices

EN

2. Plug the flat end (USB-A connector) of the provided USB device cable into the downstream port of your computer or downstream port of another hub. Plug the square end (USB-B connector) into the USB-B connector on the back of the Hub.

**Important Note:** The Hub must be connected to a USB 2.0-compliant host in order to function in high-speed mode (480Mbps data rate). If the Hub is connected to a USB 1.1-compliant host, it will operate only in low-speed or full-speed mode (1.5Mbps/12Mbps).

3. Windows will now detect your Hub and install the required driver support. (The Windows "Install New Hardware Wizard" may prompt you to provide your Windows Installation CD to complete the driver installation process).

**Important Note:** High-speed hub drivers are included with most USB 2.0 PCI upgrade cards, and are preinstalled along with the PCI card drivers. If you purchased an upgrade card prior to the release of high-speed hub support, please check with your PCI card vendor for an updated USB 2.0 driver. The Belkin USB 2.0 driver supports all competitive cards based on the NEC host controller with the exception of Adaptec. The most recent Belkin driver is available at [www.belkin.com](http://www.belkin.com).



## Connecting USB devices to the Hub

---

1. Plug the USB-A connector of the USB device(s) you wish to connect into any of the Hub's available downstream ports.
2. Follow the installation instructions provided by the manufacturer of the device.

**Important Note:** *When moving a device from one port on the Hub to another, it may be necessary to reinstall the USB drivers for that device.*

EN

## Determining the speed of connected devices

---

EN

1. The USB 2.0 specification includes three separate modes of data transmission. These are defined as low-speed (1.5Mbps), full-speed (12Mbps), and high-speed (480Mbps). The Belkin Premium hub is the only USB hub on the market today that provides a visual indication of a connected device's speed. This is accomplished using proprietary speed indication circuitry. Each downstream port on the Hub has a corresponding LED that changes color according to the speed of the connected device as noted below.

Connection Speed	LED color
Low	Green
Full	Red
High	Amber

2. In addition, the upstream port has a corresponding LED that indicates the speed of the computer's USB host controller as noted below.

Host Controller Speed	LED color
Full	Red
High	Amber

**Note:** *The Hub itself will always connect to the host as either a full- or high-speed device, never as a low-speed device.*



## FCC Statement

### DECLARATION OF CONFORMITY WITH FCC RULES FOR ELECTROMAGNETIC COMPATIBILITY

We, Belkin Corporation, of 501 West Walnut Street, Compton, CA 90220, declare under our sole responsibility that the product:

**F5U231vuk1** to which this declaration relates:

Complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

EN

## CE Declaration of Conformity

We, Belkin Corporation, declare under our sole responsibility that the F5U231vuk1, to which this declaration relates, is in conformity with Generic Emissions Standard EN 55022:1998 Class B, EN50081-1 and with Generic Immunity Standard EN50082-1 1992

## Belkin Corporation Limited Lifetime Product Warranty

Belkin Corporation warrants this product against defects in materials and workmanship for its lifetime. If a defect is discovered, Belkin will, at its option, repair or replace the product at no charge provided it is returned during the warranty period, with transportation charges prepaid, to the authorized Belkin dealer from whom you purchased the product. Proof of purchase may be required.

This warranty does not apply if the product has been damaged by accident, abuse, misuse, or misapplication; if the product has been modified without the written permission of Belkin; or if any Belkin serial number has been removed or defaced.

THE WARRANTY AND REMEDIES SET FORTH ABOVE ARE EXCLUSIVE IN LIEU OF ALL OTHERS, WHETHER ORAL OR WRITTEN, EXPRESSED OR IMPLIED. BELKIN SPECIFICALLY DISCLAIMS ANY AND ALL IMPLIED WARRANTIES, INCLUDING, WITHOUT LIMITATION, WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

No Belkin dealer, agent, or employee is authorized to make any modification, extension, or addition to this warranty.

BELKIN IS NOT RESPONSIBLE FOR SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES RESULTING FROM ANY BREACH OF WARRANTY, OR UNDER ANY OTHER LEGAL THEORY, INCLUDING BUT NOT LIMITED TO LOST PROFITS, DOWNTIME, GOODWILL, DAMAGE TO OR REPROGRAMMING OR REPRODUCING ANY PROGRAM OR DATA STORED IN OR USED WITH BELKIN PRODUCTS.

# BELKIN®

Belkin Corporation  
501 West Walnut Street  
Compton, CA, 90220-5221, USA  
+1 310 898 1100  
+1 310 898 1111 fax

Belkin Ltd.  
Express Business Park  
Shipton Way, Rushden  
NN10 6GL, United Kingdom  
+44 (0) 1933 35 2000  
+44 (0) 1933 31 2000 fax

Belkin B.V.  
Boeing Avenue 333  
1119 PH Schiphol-Rijk, Netherlands  
+31 (0) 20 654 7300  
+31 (0) 20 654 7349 fax

Belkin GmbH  
Hanebergstrasse 2  
80637 Munich, Germany  
+49 (0) 89 143405 0  
+49 (0) 89 143405 100 fax

Belkin SAS  
130 rue de Sully  
92100 Boulogne-Billancourt, France  
+33 (0) 1 41 03 14 40  
+33 (0) 1 41 31 01 72 fax

Belkin Iberia  
Avda. Cerro del Aguila 3  
28700 San Sebastián de los Reyes, Spain  
+34 9 16 25 80 00  
+34 9 02 02 00 34 fax

Please visit our website [www.belkin.com](http://www.belkin.com) for technical support or further information.

Disposal of Waste Equipment by Users in Private Households in the European Union:  
For more information, go to [www.belkin.com/environmental](http://www.belkin.com/environmental)

© 2006 Belkin Corporation. All rights reserved. All trade names are registered trademarks of respective manufacturers listed. Mac OS and Mac are trademarks of Apple Computer, Inc., registered in the U.S. and other countries.

P75250uk